



Product features and key data

| | |
|-------------------|--------|
| Net length | 81 mm |
| Net width | 81 mm |
| Net height | 14 mm |
| Weight | 0,1 kg |

Offer text

LiveLink wireless push-button with 4 rocker switches for wireless networking with a LiveLink Basic wireless network (2.4 GHz wireless mesh network).

2 rocker switches for switching and dimming the lighting as well as 2 rocker switches for calling up freely selectable light scenes.

Radio range of the push-button up to 10 m.

Battery-free and maintenance-free push-button based on ZigBee Green Power technology and a service life of at least 50,000 switching cycles.

Permissible ambient temperature -25 - +65 °C.

Housing dimensions (L x W x H) 81 mm x 81 mm x 14 mm. Suitable for adhesive installation or screw-fastening on a flat surface. Double-sided mounting foil in scope of delivery. Taster erfordert keinen Netzanschluss, Energieerzeugung durch integrierten elektrodynamischem Energieerzeuger. Commissioning and programming of the push-button functions are carried out with the LiveLink Basic Wireless Install app (iOS/Android) via Bluetooth connection with a smartphone.